

101-PT~116-PT

Our Wythe lanterns and sconces are just straight forward church fixtures. They embody a simplicity and clarity of design that you would normally only see in early colonial lights. The fixtures are hexagonal lanterns with a finely embossed decorative banding top and bottom. The crown is actually hand rolled and then capped with an acanthus leaf top band. We build these fixtures from solid brass or aluminum metals. And we offer terrific finish, diffuser, and lamping options. With our high powered LED lampings, you can look old on the outside, but work brand new on the inside.

~Wythe Series~

Chandelier:141-CHT~173-CHT

Pendant:101-PT~116-PT

Ceiling Mount:104-CT~117-CT

Wall Mount:101-WT~113-WT

S-Pendant:103-ST~115-ST

Mounting:Lightsmith fixtures mount to standard 4" octagon electrical boxes unless otherwise specified. All hardware and canopies supplied.

Listing and Warranty: Lightsmith fixtures are Underwriters Laboratories listed and carry a standard three year warranty against defects in materials and labor beginning at date of shipment.













DIFFUSER (Example: BGA-ECH)





Notes~Modifications

	Fixture Number	Dimensions	<u>Lamping</u>	Weight	Stem/Chain	<u>Options</u>
LED	☐ 101-PT	10w x 18h	2-13wL(2820 lm)	11 lbs	3' Std	IEM,REM,SPR**
	☐ 102-PT	12w x 23h	4-13wL(5640 lm)/1-38wC(5734 lm)	13 lbs	6' Std	C,G,L313
	☐ 103-PT	12w x 29h	6-13wL(8460 lm)/1-38wC(5734 lm)	17 lbs	9' Std	C,G,L313
	104-PT	14w x 35h	12-13wL(16920 lm)/1-52wC(9375 lm)	24 lbs	9' Std	C,G,L323
	☐ 105-PT	16w x 41h	12-13wL (16920 lm)/1-83wC (12597 lm)	29 lbs	12' Std	C,G,L323
INCANDESCENT	108-PT 110-PT 112-PT 114-PT 116-PT	10w x 18h 12w x 23h 12w x 29h 14w x 35h 16w x 41h	1-150wA(1200 lm) 3-75wA(3600 lm)/1-250wP38(3600 lm) 6-75wA(7200 lm)/1-250wP38(3600 lm) 6-75wA(7200 lm)/1-500wR40(5000 lm) 9-75wA(10800 lm)/1-500wR40(5000 lm)	8 lbs 10 lbs 14 lbs 21 lbs 26 lbs	3' Std 6' Std 9' Std 9' Std 12' Std	C,G,L38 C,G,L52,L310 C,G,L52,L610 C,G,L83,L610 C,G,L83,L910
FLUORESCENT			To Contact of the Con			MANUEDE

	^	Two Circuits Standard Wirir	ng~	**All LED Fixtures
DIFFUSER	BGA: Beige Alabaster Acrylic NHA: Natural Horn Acrylic WHA: White Alabaster Acrylic HNA: Honey Alabaster Acrylic WOA: White Opal Acrylic	GRA: Green E EGA: Earth Gr DGA: Deep Go SOG: Streaker WOG: White O	reen Acrylic old Acrylic d Opal Glass	*Etched* *Etched option creates a matte, non-glossy finish on one side of the diffuser. (Example:WOA-ECH)
	SOLID BRASS FINISHES PAIN	TED METAL FINISHES	ALUMINUM FINISHE	STAINLESS STEEL FINISHES
METAL FINISH	SBB: Satin Brass PBB: Polished Brass ANB: Antique Nickel SNB: Satin Nickel PNB: Polished Nickel AZB: Antique Bronze SZB: Satin Bronze PZB: Polished Bronze SCF	P: Dark Green P: Verde Green P: Charcoal Gray P: Medium Bronze P: Satin Black P: Dark Bronze P: Light Bronze P: Medium Gold P: Sponged Copper P: Custom Paint*	SAA: Satin Alum SNA: Satin Nicke PAA: Polished Alur BBA: Burnished B RNA: Red Naval E SGA: Satin Gold SBA: Satin Bron ORA: Oil Rubbed E SCA: Satin Copp CSA: Custom Alur	DSS: Distressed ninum PSS: Polished ronze HASS: Hammered ronze Ron
OPTIONS	L38: 38wLED R40 Downlight L52: 52wLED R40 Downlight B3: 83wLED R40 Downlight DIM: Dimming Driver (std) REM: Remote Emer.Driver	L313: 3-13wCLE L323: 3-23wCLE L310: 3-10wLED L610: 6-10wLED L910: 9-10wLED	D Uplight A-lamp A-lamp G	
~	METAL FINISH VOLTAGE	STEM=S+Lgth	OPTIONS	~ MODIFICATIONS

(Example:S-96")

CHAIN=C+Lgth

(Example:C-96"

NR=Not required

(Example:DIM,REM)

(Example:Custom Paint*)

Use "Notes" Box At Top To

Explain Modifications

(120V)

(277V)

(347V)

(Example: ABB)