



Kirkwall

SC-11600~SC-11611

Our Kirkwall fixtures are fine pendants, chandeliers, and sconces made for areas with classic flavor and distinguished surroundings. We build Kirkwall fixtures from non-ferrous metals, brass and aluminum. They can be solid powder coated or satin finished...even polished if the need arises. The sconces of this series are also available in wet location mounting for buildings that might need a subtle flare on either side of an exterior entrance. Overall these are some of the nicest things we make at Lightsmith. Completely new with an ultimately early twentieth century style.

~Kirkwall Series~

Chandelier: CH-11600~CH-11611

Pendant: PD-11600~PD-11631

Ceiling Mt: CL-11600~CL-11608

Wall Mt: SC-11600~SC-11611

Bollard: BL-11600~BL-11611

Mounting: Lightsmith fixtures mount to standard 4" octagon electrical boxes unless otherwise specified. All hardware and canopies supplied.

Listing and Warranty: Lightsmith fixtures are Underwriters Laboratories listed and carry a standard three year warranty against defects in materials and labor beginning at date of shipment.



Fixture Specifications

SC-116 ~

Fixture Number
(Example: SC-11600)

~

Diffuser
(Example: BGA-ECH)

~

Metal Finish
(Example: ABB)

~

Voltage
(120V)
(277V)
(347V)

~

NR

STEM=S+Lgth
(Example:S-96")
CHAIN=C+Lgth
(Example:C-96")
NR=Not required

~

Options
(Example:SPR)

SC-116

Fixture Number

Job Type

Job Name

Notes~Modifications

Fixture Number	Dimensions	Lamping	Weight	Options
<input type="checkbox"/> SC-11604	9w x 16h x 4x*	1-13wLED (1410 lumens)	10 lbs	WLM
<input type="checkbox"/> SC-11610	11w x 20h x 4.5x	2-13wLED (2810 lumens)	12 lbs	WLM
<input type="checkbox"/> SC-11611	13w x 24h x 5.5x	3-13wLED (4230 lumens)	14 lbs	WLM, SPR**
 <input type="checkbox"/> LED				
 <input type="checkbox"/> INCANDESCENT	9w x 16h x 4x*	2-60wT10 (1600 lumens)	8 lbs	WLM
 <input type="checkbox"/> SC-11600	11w x 20h x 4.5x	2-75wA (2800 lumens)	10 lbs	WLM
 <input type="checkbox"/> SC-11601	13w x 24h x 5.5x	2-100wA (3400 lumens)	12 lbs	WLM
 <input type="checkbox"/> SC-11602				
 <input type="checkbox"/> FLUORESCENT				

*ADA Fixture

~Single Circuit Standard Wiring~

**All LED Fixtures

<input type="checkbox"/> BGA: Beige Alabaster Acrylic	<input type="checkbox"/> GRA: Green Edge Acrylic	<input type="checkbox"/> ECH: Etched*
<input type="checkbox"/> NHA: Natural Horn Acrylic	<input type="checkbox"/> EGA: Earth Green Acrylic	<i>*Etched option creates a matte, non-glossy finish on one side of the diffuser. (Example: WOA-ECH)</i>
<input type="checkbox"/> WHA: White Alabaster Acrylic	<input type="checkbox"/> DGA: Deep Gold Acrylic	
<input type="checkbox"/> HNA: Honey Alabaster Acrylic	<input type="checkbox"/> WOG: White Opal Glass	
<input type="checkbox"/> WOA: White Opal Acrylic	<input type="checkbox"/> SOG: Streaked Opal Glass	

SOLID BRASS FINISHES	PAINTED METAL FINISHES	ALUMINUM FINISHES	STAINLESS STEEL FINISHES
<input type="checkbox"/> ABB: Antique Brass	<input type="checkbox"/> DGP: Dark Green	<input type="checkbox"/> SAA: Satin Aluminum	<input type="checkbox"/> NA
<input type="checkbox"/> SBB: Satin Brass	<input type="checkbox"/> VGP: Verde Green	<input type="checkbox"/> SNA: Satin Nickel	<input type="checkbox"/>
<input type="checkbox"/> PBB: Polished Brass	<input type="checkbox"/> CGP: Charcoal Gray	<input type="checkbox"/> PAA: Polished Aluminum	<input type="checkbox"/>
<input type="checkbox"/> ANB: Antique Nickel	<input type="checkbox"/> MBP: Medium Bronze	<input type="checkbox"/> BBA: Burnished Bronze	<input type="checkbox"/>
<input type="checkbox"/> SNB: Satin Nickel	<input type="checkbox"/> SBP: Satin Black	<input type="checkbox"/> RNA: Red Naval Bronze	<input type="checkbox"/>
<input type="checkbox"/> PNB: Polished Nickel	<input type="checkbox"/> DBP: Dark Bronze	<input type="checkbox"/> SGA: Satin Gold	<input type="checkbox"/>
<input type="checkbox"/> AZB: Antique Bronze	<input type="checkbox"/> LBP: Light Bronze	<input type="checkbox"/> SBA: Satin Bronze	<input type="checkbox"/>
<input type="checkbox"/> SZB: Satin Bronze	<input type="checkbox"/> MGP: Medium Gold	<input type="checkbox"/> ORA: Oil Rubbed Bronze	<input type="checkbox"/>
<input type="checkbox"/> PZB: Polished Bronze	<input type="checkbox"/> SCP: Sponged Copper	<input type="checkbox"/> SCA: Satin Copper	<input type="checkbox"/>
<input type="checkbox"/> CSB: Custom Brass*	<input type="checkbox"/> CSP: Custom Paint*	<input type="checkbox"/> CSA: Custom Aluminum*	<input type="checkbox"/>

<input type="checkbox"/> WLM: Wet Location Mounting	<input type="checkbox"/> REM: Remote Emer. Ballast*	<input type="checkbox"/> SPR: Surge protector
 <input type="checkbox"/>	 <input type="checkbox"/>	 <input type="checkbox"/>

SC-116

~

Diffuser
(Example: BGA-ECH)

~

Metal Finish
(Example: ABB)

~

Voltage
(120V)
(277V)
(347V)

~

NR

STEM=S+Lgth
(Example:S-96")
CHAIN=C+Lgth
(Example:C-96")
NR=Not required

~

Options
(Example:SPR)

~

Modifications
(Example:Custom Paint*)
Use "Notes" Box At Top To Explain Modifications