



Crandor

PD-500~PD-531

Our Crandor fixtures are simple bowls and sconces accented by a single rolled metal ring. We show cable supports in the pendant photo, but Crandor pendants can be supported by four angled stems, four straight stems, or four chains. Just mention it in the modifications box and we'll take care of the rest. The metals we use in these fixtures range from aluminum to brass to stainless steel. And we can finish them in polished, satin, and even hammered finishes. We offer 10 different acrylic options. And our CFL and LED options will make Crandor a maintenance dream.

~Crandor Series~

Chandelier: CH-500~CH-511

Pendant: PD-500~PD-531

Ceiling Mount: CL-500~CL-508

Wall Mount: SC-500~SC-511

Bollard: BL-500~BL-511

Mounting: Lightsmith fixtures mount to standard 4" octagon electrical boxes unless otherwise specified. All hardware and canopies supplied.

Listing and Warranty: Lightsmith fixtures are Underwriters Laboratories listed and carry a standard three year warranty against defects in materials and labor beginning at date of shipment.



Fixture Specifications

PD-5

Fixture Number
(Example: PD-500)

~

Diffuser
(Example: BGA-ECH)

~

Metal Finish
(Example: ABB)

~

Voltage
□ (120V)
□ (277V)
□ (347V)

~

Options
(Example:DIM,REM)

PD-5

Fixture Number

Job Type

Job Name

Notes~Modifications

Fixture Number	Dimensions	Lamping	Weight	Stem/Chain	Options
PD-509	18w x 18h	4-13wCLED	19 lbs	3' Std	DALI,IEM,TPL,FUS**
PD-510	24w x 24h	6-13wCLED	24 lbs	6' Std	L423,L623
PD-511	30w x 30h	6-23wCLED	31 lbs	9' Std	L423,L623,L311
PD-512	36w x 36h	6-38wCLED	34 lbs	9' Std	L623,L823,L611
PD-513	46w x 46h	6-52wCLED	47 lbs	12' Std	L623,L823,L611
PD-520	18w x 18h	3-100wA	14 lbs	3' Std	N250
PD-500	24w x 24h	3-150wA	20 lbs	6' Std	N300
PD-521	30w x 30h	6-100wA	25 lbs	9' Std	N300
PD-501	36w x 36h	6-150wA	30 lbs	9' Std	N500
PD-502	46w x 46h	12-150wA	42 lbs	12' Std	N500
PD-530	18w x 18h	2-42wCFT	18 lbs	3' Std	DIM,IEM,TPL,FUS*
PD-503	24w x 24h	4-42wCFT	23 lbs	6' Std	F242
PD-531	30w x 30h	6-42wCFT	30 lbs	9' Std	F242
PD-504	36w x 36h	8-42wCFT	33 lbs	9' Std	F442
PD-505	46w x 46h	10-42wCFT	46 lbs	12' Std	F442

~Two Circuits Standard Wiring~

*All Fluorescent Fixtures

**All LED Fixtures

<input type="checkbox"/> BGA: Beige Alabaster Acrylic	<input type="checkbox"/> GRA: Green Edge Acrylic	<input type="checkbox"/> ECH: Etched*	
<input type="checkbox"/> NHA: Natural Horn Acrylic	<input type="checkbox"/> EGA: Earth Green Acrylic	*Etched option creates a matte, non-glossy finish on one side of the diffuser. (Example: WOA-ECH)	
<input type="checkbox"/> WHA: White Alabaster Acrylic	<input type="checkbox"/> DGA: Deep Gold Acrylic		
<input type="checkbox"/> HNA: Honey Alabaster Acrylic	<input type="checkbox"/> SBA: Sea Blue Acrylic		
<input type="checkbox"/> WOA: White Opal Acrylic	<input type="checkbox"/> PHA: Purple Haze Acrylic		

SOLID BRASS FINISHES	PAINTED METAL FINISHES	ALUMINUM FINISHES	STAINLESS STEEL FINISHES
<input type="checkbox"/> ABB: Antique Brass	<input type="checkbox"/> DGP: Dark Green	<input type="checkbox"/> SAA: Satin Aluminum	<input type="checkbox"/> SSS: Satin
<input type="checkbox"/> SBB: Satin Brass	<input type="checkbox"/> VGP: Verde Green	<input type="checkbox"/> SNA: Satin Nickel	<input type="checkbox"/> DSS: Distressed
<input type="checkbox"/> PBB: Polished Brass	<input type="checkbox"/> CGP: Charcoal Gray	<input type="checkbox"/> PAA: Polished Aluminum	<input type="checkbox"/> PSS: Polished
<input type="checkbox"/> ANB: Antique Nickel	<input type="checkbox"/> MBP: Medium Bronze	<input type="checkbox"/> BBA: Burnished Bronze	<input type="checkbox"/> HSS: Hammered
<input type="checkbox"/> SNB: Satin Nickel	<input type="checkbox"/> SBP: Satin Black	<input type="checkbox"/> RNA: Red Naval Bronze	
<input type="checkbox"/> PNB: Polished Nickel	<input type="checkbox"/> DBP: Dark Bronze	<input type="checkbox"/> SGA: Satin Gold	
<input type="checkbox"/> AZB: Antique Bronze	<input type="checkbox"/> LBP: Light Bronze	<input type="checkbox"/> SBA: Satin Bronze	
<input type="checkbox"/> SZB: Satin Bronze	<input type="checkbox"/> MGP: Medium Gold	<input type="checkbox"/> ORA: Oil Rubbed Bronze	
<input type="checkbox"/> PZB: Polished Bronze	<input type="checkbox"/> SCP: Sponged Copper	<input type="checkbox"/> SCA: Satin Copper	
<input type="checkbox"/> CSB: Custom Brass*	<input type="checkbox"/> CSP: Custom Paint*	<input type="checkbox"/> CSA: Custom Aluminum*	<input type="checkbox"/> CSS: Custom SS*

<input type="checkbox"/> N250: 250wPar38 Downlight	<input type="checkbox"/> L311: 3-11wCLED Uplight	<input type="checkbox"/> FUS: Fusing
<input type="checkbox"/> N300: 300wPar56 Downlight	<input type="checkbox"/> L611: 6-11wCLED Uplight	<input type="checkbox"/> IEM: Integral Emer.Ballast
<input type="checkbox"/> N500: 500wPar56 Downlight	<input type="checkbox"/> L423: 4-23wCLED Downlight	<input type="checkbox"/> DALI: Dali dimming LED
<input type="checkbox"/> DIM: Dimming Ballast	<input type="checkbox"/> L623: 6-23wCLED Downlight	<input type="checkbox"/> F242: 2-42wCFT Downlight
<input type="checkbox"/> TPL: Top Lens	<input type="checkbox"/> L823: 8-23wCLED Downlight	<input type="checkbox"/> F442: 4-42wCFT Downlight

MODIFICATIONS

(Example:Custom Paint*)
Use "Notes" Box At Top To Explain Modifications