



101 ____ -ST

Fixture Number

Job Type

Job Name

Notes~Modifications

10102-ST~10124-ST

Our Middleton fixtures are just completely ornate gothic church lanterns and sconces. They feature thick, richly detailed metal castings that are right out of the best of historic European cathedral stone work. The result is an astonishing work of art. Fixtures such as these are few and far between and feature many choices of metal types and finishes, as well as an array of glass or acrylic diffuser lenses. The lights may be ordered in solid brass and then polished or antiqued, or solid aluminum and then satin finished, etc. Please consider our LED options. Long life clusters will be good friends.

Middleton Series~

Chandelier:10141-CHT~10173-CHT

Pendant:10101-PT~10117-PT

Ceiling Mt:10104-CT~10117-CT

Wall Mt:10101-WT~10113-WT

S-Pendant:10102-ST~10124-ST

Mounting: Lightsmith fixtures mount to standard 4" octagon electrical boxes unless otherwise specified. All hardware and canopies supplied.

Listing and Warranty: Lightsmith fixtures are Underwriters Laboratories listed and carry a standard three year warranty against defects in materials and labor beginning at date of shipment.



Fixture Specifications

101 ____ -ST

FIXTURE NUMBER
(Example: 10102-ST)

DIFFUSER
(Example: BGA-ECH)

OPTIONS

- DIM: Dimming Driver (std)
- REM: Remote Emer. Ballast
- IEM: Integral Emer. Ballast

- L131: 3-13wCLED Uplight
- L323: 3-23wCLED Uplight
- L23: 23w LED R40 Dnlt
- L38: 38w LED R40 Dnlt
- L52: 52w LED R40 Dnlt

SPR: Surge Protector

~

METAL FINISH
(Example: ABB)

~

VOLTAGE
(120V)
(277V)
(347V)

~

STEM=S+Lgth
(Example:S-96")
CHAIN=C+Lgth
(Example:C-96")
NR=Not required

~

OPTIONS
(Example:DIM,REM)

~

MODIFICATIONS
(Example:Custom Paint*)
Use "Notes" Box At Top To Explain Modifications

Fixture Number	Dimensions	Lamping	Weight	Stem/Chain	Options
<input type="checkbox"/> 10102-ST	20w x 12h	4-13wLED (5640 lm)/1-23wCLED (2790 lm)	21 lbs	3' Std	L313,L38
<input type="checkbox"/> 10103-ST	24w x 15h	6-13wLED (8460 lm)/1-38wCLED (5734 lm)	28 lbs	3' Std	L323,L52
<input type="checkbox"/> 10120-ST	20w x 12h	6-60wA (4800 lm)/1-150wP38 (1700 lm)	19 lbs	3' Std	L23,L38
<input type="checkbox"/> 10124-ST	24w x 15h	6-100wA (10440 lm)/1-250wP38 (3600 lm)	25 lbs	3' Std	L38,L52

~Two Circuits Standard Wiring~

**All LED Fixtures

<input type="checkbox"/> BGA: Beige Alabaster Acrylic	<input type="checkbox"/> GRA: Green Edge Acrylic	<input type="checkbox"/> ECH: Etched*
<input type="checkbox"/> NHA: Natural Horn Acrylic	<input type="checkbox"/> EGA: Earth Green Acrylic	*Etched option creates a matte, non-glossy finish on one side of the diffuser. (Example:WOA-ECH)
<input type="checkbox"/> WHA: White Alabaster Acrylic	<input type="checkbox"/> DGA: Deep Gold Acrylic	
<input type="checkbox"/> HNA: Honey Alabaster Acrylic	<input type="checkbox"/> SOG: Streaked Opal Glass	
<input type="checkbox"/> WOA: White Opal Acrylic	<input type="checkbox"/> WOG: White Opal Glass	

<input type="checkbox"/> SOLID BRASS FINISHES	<input type="checkbox"/> PAINTED METAL FINISHES	<input type="checkbox"/> ALUMINUM FINISHES	<input type="checkbox"/> STAINLESS STEEL FINISHES
<input type="checkbox"/> ABB: Antique Brass	<input type="checkbox"/> DGP: Dark Green	<input type="checkbox"/> SAA: Satin Aluminum	<input type="checkbox"/> NA
<input type="checkbox"/> SBB: Satin Brass	<input type="checkbox"/> VGP: Verde Green	<input type="checkbox"/> SNA: Satin Nickel	<input type="checkbox"/>
<input type="checkbox"/> PBB: Polished Brass	<input type="checkbox"/> CGP: Charcoal Gray	<input type="checkbox"/> PAA: Polished Aluminum	<input type="checkbox"/>
<input type="checkbox"/> ANB: Antique Nickel	<input type="checkbox"/> MBP: Medium Bronze	<input type="checkbox"/> BBA: Burnished Bronze	<input type="checkbox"/>
<input type="checkbox"/> SNB: Satin Nickel	<input type="checkbox"/> SBP: Satin Black	<input type="checkbox"/> RNA: Red Naval Bronze	<input type="checkbox"/>
<input type="checkbox"/> PNB: Polished Nickel	<input type="checkbox"/> DBP: Dark Bronze	<input type="checkbox"/> SGA: Satin Gold	<input type="checkbox"/>
<input type="checkbox"/> AZB: Antique Bronze	<input type="checkbox"/> LBP: Light Bronze	<input type="checkbox"/> SBA: Satin Bronze	<input type="checkbox"/>
<input type="checkbox"/> SZB: Satin Bronze	<input type="checkbox"/> MGP: Medium Gold	<input type="checkbox"/> ORA: Oil Rubbed Bronze	<input type="checkbox"/>
<input type="checkbox"/> PZB: Polished Bronze	<input type="checkbox"/> SCP: Sponged Copper	<input type="checkbox"/> SCA: Satin Copper	<input type="checkbox"/>
<input type="checkbox"/> CSB: Custom Brass*	<input type="checkbox"/> CSP: Custom Paint*	<input type="checkbox"/> CSA: Custom Aluminum*	<input type="checkbox"/>

<input type="checkbox"/> DIM: Dimming Driver (std)	<input type="checkbox"/> L131: 3-13wCLED Uplight	<input type="checkbox"/> SPR: Surge Protector
<input type="checkbox"/> REM: Remote Emer. Ballast	<input type="checkbox"/> L323: 3-23wCLED Uplight	<input type="checkbox"/>
<input type="checkbox"/> IEM: Integral Emer. Ballast	<input type="checkbox"/> L23: 23w LED R40 Dnlt	<input type="checkbox"/>
	<input type="checkbox"/> L38: 38w LED R40 Dnlt	<input type="checkbox"/>
	<input type="checkbox"/> L52: 52w LED R40 Dnlt	<input type="checkbox"/>